

inReach Support Center


Portal > Knowledgebase > Enterprise Web Portal [enterprise.delorme.com] > Enterprise Portal > How-To > Managing Profiles for inReach Enterprise

Managing Profiles for inReach Enterprise

Lu Parente - 2016-01-19 - 0 Comments - in How-To

The Enterprise web portal now allows Administrators to create standard device profiles to be applied to each of their devices. These profiles can be created for specific sub-groups, or can be applied to all devices on the account. Assigning a profile lets the account Administrator control which icons appear on the devices' menu, what the standard device setup options presented will be, and also controls if the user can access any the options at all.

1. To begin using Profiles on your account, navigate to the Groups & Users tab and select Manage Profiles.



2. You now have the ability to customize the existing profile or create as many additional profiles as you desire for both device types, inReach SE and inReach Explorer.

a. To customize the existing profile, select the desired device type, drag and drop the icons amongst any of the 3 screens displayed. Icons can also be removed entirely by dragging them to the Removed from inReach section. Select Save Changes when finished.

Note: The SOS button cannot be removed from the menu, only moved to a different screen.

b. To create a new profile, select New Profile, and give your profile a name.

c. To reset or undo all changes to a specific device profile, select Restore Defaults.

Done Manage Profiles
Profiles are saved sets of inReach SE and Explorer settings. [More](#)

New Profile Copy Delete

SAVED PROFILES
inReach Tech Support Profile

inReach Tech Support Profile

Save Changes Cancel Changes

Home Screen Icons: Drag and drop to adjust [Restore Defaults](#)

inReach Explorer inReach SE

First screen			Second screen			Third screen		
Routes	Tracking	Trip Info	Check	Contacts	Location			
Map	Messages	Waypoints	Preset	Data Use	Help			
Social	Compass	SOS	Settings	History				

Removed from inReach

Forms								

3. Device settings can also be configured for all devices with this profile. Here you can configure the default settings as well as the settings presented to the device user. You can also remove options from the device, or completely hide the ability to modify an option.

- a. Expand the desired inReach Setting from the menu below and make any necessary changes.
- b. Once all profile settings have been setup as per your requirements, select Save Changes at the top of the screen followed by Done.

inReach Settings	Visible on inReach	Values	Restore Defaults
⊖ Display			
Screen Lock		<input type="radio"/> Off <input checked="" type="radio"/> On	
Display Timer	<input checked="" type="checkbox"/>	<i>Default</i> <i>Set which are available on inReach</i> <input type="radio"/> <input checked="" type="checkbox"/> 15 seconds (best battery) <input checked="" type="radio"/> <input checked="" type="checkbox"/> 30 seconds <input type="radio"/> <input checked="" type="checkbox"/> 45 seconds <input type="radio"/> <input checked="" type="checkbox"/> 1 minute <input type="radio"/> <input checked="" type="checkbox"/> 2 minutes <input type="radio"/> <input checked="" type="checkbox"/> 5 minutes (longest view)	
Always on with Ext Power	<input checked="" type="checkbox"/>	<input type="radio"/> Off <input checked="" type="radio"/> On	
+ Tracking			
+ Bluetooth			
+ Messages			
+ Sounds			
+ Time			
+ Units			
+ Power			
+ Owner Info			

4. Now that you've finished creating or customizing a profile, you must assign the profile to your Users accounts, and perform a sync. [Click here for assistance with assigning a profile to a User or a Group of users.](#)

Related Pages

- [Enabling Team Tracking for inReach Enterprise](#)